on button, high-voltage off button, high-voltage	PAGE 1 OF 1 THIS HIGH-VOLTAGE TESTER IS IDEAL FOR TESTING HIGH-VOLTAGE CABLES, SWITCHGEAR, HIGH-VOLTAGE TRANSFORMERS, ELECTRIC MOTORS AND SIMILAR EQUIPMENT.	
DV-100VA-10V-01INPUT120 V 60 Hz Single-PhaseOUTPUTAdjustable 0-10 kV dc @ 10 mATRIP CURRENTAdjustable 3 -10 mAMETERSOne voltmeter 0-10 kV dc and one ammeter 0-10 mAO-10 mAAccuracy of both meters: ±2% of full scaleINDICATORS5 Lights (Power-on, High-Voltage on, Off Zero Start, Fault and Line-Fault)CONTROLSPower on/off switch, fuse, reset-button, high-voltage on button, high-voltage off button, high-voltage		PORTABLE HIGH-VOLTAGE TESTER
OUTPUTAdjustable0-10 kV dc @ 10 mATRIP CURRENTAdjustable 3 -10 mAMETERSOne voltmeter0-10 kV dc and one ammeter0-10 mAAccuracy of both meters: ±2% of full scaleINDICATORS5 Lights (Power-on, High-Voltage on, Off Zero Start, Fault and Line-Fault)CONTROLSPower on/off switch, fuse, reset-button, high-voltageon button, high-voltage off button, high-voltage		SPECIFICATIONS
OUTPUTAdjustable0-10 kV dc @ 10 mATRIP CURRENTAdjustable 3 -10 mAMETERSOne voltmeter0-10 kV dc and one ammeter0-10 mAAccuracy of both meters: ±2% of full scaleINDICATORS5 Lights (Power-on, High-Voltage on, Off Zero Start, Fault and Line-Fault)CONTROLSPower on/off switch, fuse, reset-button, high-voltage on button, high-voltage off button, high-voltage	INPUT	120 V 60 Hz Single-Phase
TRIP CURRENTAdjustable 3 -10 mAMETERSOne voltmeter 0-10 kV dc and one ammeter 0-10 mAO-10 mAAccuracy of both meters: ±2% of full scaleINDICATORS5 Lights (Power-on, High-Voltage on, Off Zero Start, Fault and Line-Fault)CONTROLSPower on/off switch, fuse, reset-button, high-voltage on button, high-voltage off button, high-voltage	OUTPUT	
0-10 mAAccuracy of both meters: ±2% of full scaleINDICATORS5 Lights (Power-on, High-Voltage on, Off Zero Start, Fault and Line-Fault)CONTROLSPower on/off switch, fuse, reset-button, high-voltage on button, high-voltage off button, high-voltage	TRIP CURRENT	Adjustable 3-10 mA
INDICATORS5 Lights (Power-on, High-Voltage on, Off Zero Start, Fault and Line-Fault)CONTROLSPower on/off switch, fuse, reset-button, high-voltage on button, high-voltage off button, high-voltage	METERS	
on button, high-voltage off button, high-voltage	INDICATORS	5 Lights (Power-on, High-Voltage on, Off Zero Start,
	CONTROLS	Power on/off switch, fuse, reset-button, high-voltage on button, high-voltage off button, high-voltage adjust dial c/w zero start position, trip current adjust dial, safety device for incorrectly wired power outlet
LEADS One input line-cord 2 meters (6 ft.) long), one high- voltage lead 3 meters (10 ft.) long and one ground lead 3 meters (10 ft.) long.	LEADS	One input line-cord 2 meters (6 ft.) long), one high- voltage lead 3 meters (10 ft.) long and one ground
SIZE 48W x 41D x 25H cm (19W x 16D x 10H inches)	SIZE	48W x 41D x 25H cm (19W x 16D x 10H inches)
WEIGHT 18 kg (40 lb)	WEIGHT	18 kg (40 lb)

NOTE: 95% of all parts and components in this tester are made in Canada and USA

Manufactured by: Criterion Instruments Limited.